

## **TPL-001-AB-0 System Performance Under Normal Conditions**

### **1. Purpose**

The purpose of this *reliability standard* is to ensure that a reliable transmission system is planned that meets specified performance requirements, with sufficient lead time. The transmission system must continue to be modified or upgraded as required to meet present and future system specified performance requirements as identified by periodically performed system simulations and associated planning assessments.

### **2. Applicability**

This *reliability standard* applies to:

- *ISO*

### **3. Definitions**

Italicized terms used in this *reliability standard* have the meanings as set out in the Alberta Reliability Standards Glossary of Terms and Part 1 of the ISO Rules.

### **4. Requirements**

**R1** The *ISO* must demonstrate through a planning assessment that a transmission system is planned such that, with all *transmission facilities* in service and with *pre-contingency* operating procedures in effect, the transmission system can be operated to accommodate forecasted customer *demands*, supply and forecasted *firm* (non-recallable reserved) transmission services at all *demand* levels over the range of forecast system *demands*, under the conditions defined in Category A of Appendix 1.

The *ISO* planning assessment must:

**R1.1** Be carried out annually.

**R1.2** Be conducted for years one through five and years six through ten planning horizons.

**R1.3** Be supported by a study and/or system simulation testing, conducted within the last five years, that addresses each of the requirements in requirement R1.3.1 to R1.3.9, showing system performance for the conditions defined in Category A of Appendix 1.

**R1.3.1** Cover critical system conditions and study years as determined necessary by the *ISO*.

**R1.3.2** Be conducted annually unless the *ISO* determines that changes to system conditions do not warrant such analyses.

**R1.3.3** Be conducted beyond the five year planning horizon only as needed to address identified marginal conditions that may have longer lead time solutions.



---

## TPL-001-AB-0 System Performance Under Normal Conditions

---

- A certification that the planning assessment complies with each of the R1 technical requirements is provided and states that the planning assessment meets all requirements, identifies requirements not met, and states reasons where the requirement was not met.
- A summary list of supporting area studies and needs identification documents is provided. The summary list includes the title and date of the study. The area studies and needs identification documents are provided if requested.

**MR2** The area studies and needs identification documents contain recommendations and projects for corrective plans where an inability of the systems to respond to requirements specified in R1 has been identified. The area studies and needs identification documents are provided on request. The area studies and needs identification documents contain the technical components as specified in R2 and its subsections.

**MR3** A written or email confirmation from *WECC* that it has received the planning assessment from the *ISO*. The confirmation includes the date of when the planning assessment was received and source identification information.

### 7. Appendices

**Appendix 1 - Transmission System Standards – Normal and Emergency Conditions**  
(see below)

### 8. Guidelines

No guidelines have been defined for this *reliability standard*.

### Revision History

Effective	Description
0000-00-00	
0000-00-00	

**TPL-001-AB-0 System Performance Under Normal Conditions**

**Appendix 1 - Transmission System Standards – Normal and Emergency Conditions**

Category	Contingencies	System Limits or Impacts		
	Initiating Event(s) and Contingency Element(s)	System Stable and Both Thermal and Voltage Limits Within Applicable Rating <sup>a</sup>	Loss of Demand or Curtailed Firm Transmission Service Transfers	Cascading
<b>A</b> No contingencies	All facilities in service	Yes	No	No
<b>B</b> Event resulting in the loss of a single element	Single Line Ground (SLG) or 3-Phase (3Ø) fault, with normal clearing: 1. Generator 2. Transmission circuit 3. Transformer	Yes Yes Yes Yes	No <sup>b</sup> No <sup>b</sup> No <sup>b</sup> No <sup>b</sup>	No No No No
<b>C</b> Event(s) resulting in the loss of two or more (multiple) elements	SLG fault, with normal clearing <sup>e</sup> : 1. Bus section 2. Breaker (failure or internal fault)	Yes Yes	Planned/ Controlled <sup>c</sup> Planned/ Controlled <sup>c</sup>	No No
	SLG or 3Ø fault, with normal clearing <sup>e</sup> , manual system adjustments, followed by another SLG or 3Ø fault, with normal clearing <sup>e</sup> 3. Category B (B1, B2, B3, or B4) contingency, manual system adjustments, followed by another Category B (B1, B2, B3, or B4) contingency	Yes	Planned/ Controlled <sup>c</sup>	No
	Bipolar block, with normal clearing <sup>e</sup> :			
	4. Bipolar (dc) line fault (non 3Ø), with normal clearing <sup>e</sup> : 5. Any two circuits of a multiple circuit towerline <sup>f</sup>	Yes Yes	Planned/ Controlled <sup>c</sup> Planned/ Controlled <sup>c</sup>	No No
	SLG fault, with delayed clearing <sup>e</sup> (stuck breaker or protection system failure) 6. Generator 7. Transformer	Yes Yes	Planned/ Controlled <sup>c</sup> Planned/ Controlled <sup>c</sup>	No No
	8. Transmission circuit	Yes	Planned/ Controlled <sup>c</sup>	No
	9. Bus section	Yes	Planned/ Controlled <sup>c</sup>	No

## TPL-001-AB-0 System Performance Under Normal Conditions

<p><b>D<sup>d</sup></b></p> <p>Extreme event resulting in two or more (multiple) <i>elements</i> removed or <i>cascading</i> out of service</p>	<p>3Ø fault, with delayed clearing<sup>e</sup> (stuck breaker or <i>protection system</i> failure):</p> <table style="width: 100%; border: none;"> <tr> <td style="width: 50%;">1. Generator</td> <td style="width: 50%;">2. Transmission circuit</td> </tr> <tr> <td>3. Transformer</td> <td>4. Bus section</td> </tr> </table>	1. Generator	2. Transmission circuit	3. Transformer	4. Bus section	<p>Evaluate for risks and consequences</p> <ul style="list-style-type: none"> <li>• May involve substantial loss of customer demand and generation in a widespread area or areas</li> <li>• Portions or all of the <i>interconnected</i> systems may or may not achieve a new, stable operating point</li> <li>• Evaluation of these events may require joint studies with neighboring systems</li> </ul>
	1. Generator	2. Transmission circuit				
	3. Transformer	4. Bus section				
<p>3Ø fault, with <i>normal clearing</i><sup>e</sup>:</p> <p>5. Breaker (failure or internal fault)</p>						
<p>6. Loss of towerline with three or more circuits</p> <p>7. All transmission lines on a common right-of-way</p> <p>8. Loss of a substation (one voltage level plus transformers)</p> <p>9. Loss of a switching station (one voltage level plus transformers)</p> <p>10. Loss of all generating units at a station</p> <p>11. Loss of a large <i>load</i> or major <i>load</i> center</p> <p>12. Failure of a fully redundant <i>special protection system</i> (or <i>remedial action scheme</i>) to operate when required</p> <p>13. Operation, partial operation, or <i>misoperation</i> of a fully redundant <i>special protection system</i> (or <i>remedial action scheme</i>) in response to an event or abnormal system</p> <p>14. Impact of severe power swings or oscillations from disturbances in another Regional Reliability Organization</p>						

- a) Applicable *rating* refers to the applicable normal and emergency *facility* thermal and voltage *rating* as applied by the *facility* owner or system voltage limit as determined and consistently applied by the ISO. Applicable *ratings* may include emergency *ratings* applicable for short durations as required to permit operating steps necessary to maintain system control. All *ratings* must be established by the applicable entity consistent with applicable ISO rules addressing *facility ratings*.
- b) Planned or controlled interruption of electric supply to radial customers or some local network customers, connected to or supplied by the faulted *element* or by the affected area, may occur in certain areas without impacting the overall *reliability* of the *interconnected* transmission systems. To prepare for the next *contingency*, system adjustments are permitted, including curtailments of contracted firm (non-recallable reserved) transmission service electric power transfers.
- c) Depending on system design and expected system impacts, the controlled interruption of electric supply to customers (*load* shedding), the planned removal from service of certain generators, and/or the curtailment of contracted firm (non-recallable reserved) transmission service electric power transfers may be necessary to maintain the overall *reliability* of the *interconnected* transmission systems.
- d) A number of extreme *contingencies* that are listed under Category D and judged to be critical by the transmission planning entity(ies) will be selected for evaluation. It is not expected that all possible *facility outages* under each listed *contingency* of Category D will be evaluated.

## **TPL-001-AB-0 System Performance Under Normal Conditions**

---

- e) *Normal clearing* is when the *protection system* operates as designed and the fault is cleared in the time normally expected with proper functioning of the installed *protection systems*. Delayed clearing of a fault is due to failure of any *protection system* component such as a relay, circuit breaker, or current transformer, and not because of an intentional design delay.
- f) System assessments may exclude these events where multiple circuit towers are used over short distances (i.e., station entrance, river crossings) in accordance with exemption criteria.