

ISO Rules

Part 200 Markets

Division 202 Dispatching the Markets

Section 202.5 Supply Surplus



Draft Version
Posted January 2019

Applicability

- 1 Section 202.5 applies to:
- (a) a **pool participant**; and
 - (b) the **ISO**.

Requirements

State of Supply Surplus and Multiple Zero Dollar (\$0) Offers

2(1) Subject to subsection 2(2), if the **ISO** determines that a state of supply surplus is imminent or already exists, as evidenced by the in merit electricity supply consisting of only multiple \$0.00 **offers** and the supply of electricity available from these **offers** exceeds the **system load**, then the **ISO** must comply with the following procedures as may be required, in the following sequence, to balance system supply and **system load**:

- (a) allow **pool participants** to submit **bids** to increase export **interchange transactions** within two (2) hours of the start of a **settlement interval**;
- (b) allow **pool participants** to submit **offers** to decrease import **interchange transactions** within two (2) hours of the start of a **settlement interval**;
- (c) allow **pool participants** to submit restatements reducing **generating unit** and **aggregated generating facility** output, or increasing load **sink asset** consumption, within two (2) hours of the start of a **settlement interval**;
- (d) issue **dispatches** in accordance with Section 202.3 of the **ISO rules**, *Issuing Dispatches for Equal Prices*;
- (e) if there are **generating units** and **aggregated generating facilities** with \$0 **offers** for **inflexible blocks** stating volumes greater than their declared **minimum stable generation**, then issue **directives** to curtail those **generating units** and **aggregated generating facilities** to their declared **minimum stable generation**, starting with the **generating units** and **aggregated generating facilities** having the greatest difference in MW between the then current **dispatch** level and **minimum stable generation** and continuing in descending order until all those **generating units** and **aggregated generating facilities** have received **directives**; and
- (f) issue **directives** for any other necessary actions, including shutting down **generating units** and **aggregated generating facilities**, to ensure system **reliability**.

(2) If the **ISO** determines that a **generating unit** or **aggregated generating facility** is running at a generation level higher than its **minimum stable generation** in order to provide **regulating reserve**, then the **ISO** may, as part of the effective execution of the procedures set out in subsection 2(1), issue a **dispatch** to curtail delivery of **regulating reserve** from that **generating unit** or **aggregated generating facility** and issue a **dispatch** for **regulating reserve** to another **generating unit** or **aggregated generating facility** which can provide **regulating reserve** while operating at a lower generation level at or above **minimum stable generation**.

(3) If during a current hour the present, real time operating conditions change such that the **ISO** determines that following the procedural sequence set out in subsections 2(1) and 2(2) would put the **ISO** in contravention of any **reliability standard** requirement by failing to achieve compliance within the

ISO Rules

Part 200 Markets

Division 202 Dispatching the Markets

Section 202.5 Supply Surplus



operating limits or required response time specified in that **reliability standard**, then the **ISO** may alter the procedural sequence.

(4) If the **ISO** alters the procedural sequence as set out in subsection 2(3), then once the **ISO** is assured that the **interconnected electric system** is operating in a safe and reliable mode, the **ISO** must recommence the procedural sequence set out in subsections 2(1) and 2(2).

Transitioning Out of a State of Supply Surplus

3 When the **ISO** determines that the **interconnected electric system** is transitioning out of a state of supply surplus, the **ISO** must reverse any actions taken under subsection 2(1), in reverse order, to balance system supply and **system load**.

Revision History

Date	Description
xxxx-xx-xx	Clarified references to import interchange transactions, added reference to load, added reference to section 202.3, and administrative revisions.
2018-09-01	Revised “source asset” to “generating unit or aggregated generating facility”; clarified subsections 2 and 3; and administrative revisions.
2012-03-28	Initial release